



















Kompatibilitätsliste Dimmer

Kompatibel: kein Flackern,
keine Geräusche

Semi-kompatibel: kein
Flackern, ggf. Geräusche

Inkompatibel: ggf.
Flackern, ggf. Geräusche

Dimmer brand	Type	Max. load	Spot RA HQ Dim		Downlight HZ ^{DIM}				Spot Ava G2		Spot 3C Compact
			7W	8W	7W	10W	13W	16W	5W	7W	12W
											
ABB	2250 AJ-513	60 - 600W		2-11					2-6	2-6	
Berker	286610	20-500W	1-13	1-5	1-13	1-10	1-7	1-6			
Berker	2819	60-400W		1-10							1-9
Berker	2830 10	60-400W	1-10			1-8	1-6	1-5			1-9
Bticino	L-N-NT4411N	3-400W	1-11	1-11	1-11	1-11	1-6	1-5			1-5
BULL	B6GD100	500W				1-10	1-7	1-6			1-13
BUSCH-JAEGER	6523U	LED typical 2 ... 100W	1-13	1-11	1-13	1-10	1-7	1-6	1-14	1-11	1-7
BUSCH-JAEGER	6513 U-102	40 - 420W	1-11	1-9	1-11	1-8		1-5			1-11
BUSCH-JAEGER	2247U	20 - 500W		1-11	1-13	1-10	1-7	1-6			1-11
BUSCH-JAEGER	6524U	LED 2 - 100 W	1-13	2-5	1-13	1-10	1-7	1-6			
BUSCH-JAEGER	2250U	600W	1-16	2-11	1-16	1-12	1-9	1-7			1-14
BUSCH-JAEGER	6591 U-101-500	420W	1-13	1-12	1-11	1-11	1-7	1-6			
BUSCH-JAEGER	6523 UR-103	2-400W	1-11	1-10	1-11	1-11	1-6	1-5	1-11	1-9	
Busch	6523U-102	10-250W/LED2-100W	1-13		1-13	1-10	1-7	1-6			1-9
Busch	6526U	10-200W/LED2-100W					1-7				
Eltako	EUD61NPN-UC	400W		1-9							
EFAPPEL	21215	3-50W	1-6	1-6	1-6	1-5	1-3	1-3			
EFAPPEL	21214	3-35W	1-4	1-4	1-4	1-3	1-2	1-2	1-5	1-4	1-2
EFAPPEL	21216	3-85W	1-11	1-10	1-11	1-8	1-6	1-5			
EPV	PAB 315	20-315W	1-8	1-7	1-8	1-6	1-4	1-4			1-11
Feller	40200 LED FMI 61	4-200W/VA	1-5	1-5	1-5	1-3	1-3	1-2		1-5	
Feller	40600 RL FIM61	20-300W/VA	1-8	1-7	1-7	1-5	1-4	1-3		1-7	1-13
Feller	40300 RC FMI 61	40-600VA/W	1-16	1-7							1-9
Feller	40600 RLC FMI 61	20-600VA/W		1-15	1-15	1-11	1-8	1-7		1-12	1-13
GIRA	UNIV 420WV	50 VA - 420 VA		1-9							
GIRA	HAL/LED 500VA	20 VA - 500 VA									
GIRA	117600/104	50-420W	1-11		1-11	1-8	1-6	1-5			1-13
GIRA	226200/101	20-500W/LED3-100W	1-13		1-13	1-10	1-7	1-6			1-8
GIRA	0302 00/101	60-600W	1-16		1-16	1-12	1-9	1-7			
GIRA	0307 00/102	20-525W	1-14		1-14	1-10		1-6	1-15	1-11	1-11
GIRA	245000 00/101	3-60W									
JUNG	225 NV DE	20-500W/LED3-100W	1-13	1-3	1-13	1-10	1-7	1-6			
JUNG	266 G DE	60-600W	1-16	1-3	1-16	1-12	1-9	1-7			
JUNG	1731DD	3-420VA									
JUNG	1730DD	3-210VA									
Klemko	891040	315W		1-5							
Kopp	809500008	40-400W/VA									
Legrand	617 030	40-600w	1-16			1-12		1-7			
merten	MEG5134-0000	4-400W	1-10	1-10	1-11	1-8	1-6	1-5			1-13
NIKO	310-0190X	5-325W	1-8	1-13	1-9	1-6	1-4	1-4			1-13
NIKO	310-02900	3-300W	1-8		1-8	1-6	1-4	1-3	1-8	1-7	
NIKO	310-0490X	4-200W	1-6	1-5	1-6	1-6	1-3	1-3			
NIKO	310-0390X	3-200W	1-5	1-5	1-5	1-5	1-3	1-2	1-5	1-5	
NIKO	310-0280X	2-100W	1-3	1-12	1-2	1-3	1-7	1			1-7
NVC	EP8D11A BLB5	400W	1-10	1-9	1-11	1-8	1-6	1-5			1-11
OPUS	852,397	7-110W/LED3-35W	1-4	1-4	1-4	1-3	1-2	1-2	1-5	1-3	1-2
PEHA	TRONIC-DIMMER 435 HAB	20-600W	1-16	1-10	1-16	1-12	1-7	1-7	1-17	1-2	1-8
PEHA	D 431HAN LED	6-120W/LED6-60W	1-8	1-7	1-8	1-6	1-4	1-4	1-8	1-7	1-7
TRUMP	DIMMAX 420SL	400W		1-10							
Panasonic	BS EN 60669-2-1	150-500W				1-10	1-7	1-6			1-11
Panasonic	WEG578153	80-500W	1-13		1-13	1-10	1-7	1-6			1-11
SIEMENS	5UH8222-3NC01	40-500W	1-13	1-11	1-13	1-10	1-7	1-6	1-14		1-13





Dimmer brand	Model	Type	Max. load	Filament											
				A60	A60	G45	G45	P45	P45	B35	B35	ST64	ST64	ST64	ST64
				470lm	806lm	250lm	470lm	250lm	470lm	250lm	470lm	470lm	806lm	400lm	700lm
															
Berker	286610	RL	500W	1-20	1-20	2-10	1-20	2-10	1-20	2-10	1-20	1-20	1-20	1-20	1-20
Berker	2819	R	400W	1-20	1-20	1-20	1-20		1-20		1-20	1-20	1-20	1-20	1-20
Berker	283010	R	400W	1-20	1-20	1-12	1-20	1-12	1-20	1-12	1-20	1-20	1-20	1-20	1-20
Bticino	N4411N		400W/75W (LED)	1-20	1-10	1-16	1-20	2-20	1-20	2-20	1-20	1-20	1-10	1-20	1-10
Busch Jaeger	2247U	RL	500W	1-20	1-20	2-20	1-20	2-20	1-20	2-20	1-20	1-20	1-20	1-20	1-20
Busch Jaeger	2250U	R	600W	1-20	1-20	1-12	1-20	1-12	1-20	1-12	1-20	1-20	1-20	1-20	1-20
Busch Jaeger	6513 U-102	RC	40-420W	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20
Busch Jaeger	6523U	R,L	100W	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20
Busch Jaeger	6523 U-102	R,C	250W	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20
Busch Jaeger	6591 U-101-500		60-420W	1-20	1-18	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-18	1-20	1-18
Busch Jaeger	6523 UR-103		2-400W	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20
Druck	8095	RL	400W	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20
EFAPEL	21212		250W/85W (LED)	1-18	1-12	1-20	1-18		1-20		1-20	1-18	1-12	1-18	1-12
EFAPEL	21214		110W/35W (LED)	1-7	1-5	1-7	1-7	1-12	1-12	1-12	1-12	1-7	1-5	1-7	1-5
EFAPEL	21215		150W/50W (LED)	2-11	4-7		2-11		1-17		1-17	2-11	4-7	2-11	4-7
EFAPEL	21216		5-150W (LED)					1-20	1-10	1-20	1-10				
EPV	PAB 315		315W	1-20	2-12	2-20	1-20		1-20		1-20	1-20	2-12	1-20	2-12
Feller	40200 LED FMI 61		400W	1-20	1-16	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-16	1-20	1-16
Feller	40600 RL FIM61		40-600W	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20
Feller	40300 RC FMI 61		20-300W	1-20	1-16	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-16	1-20	1-16
Feller	40600 RLC FMI 61		20-600W	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20
Gira	1176 00/104	R,L,C	420W	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20
Gira	2262 00/101	R,L	500W	1-20	1-20	2-20	1-20	2-20	1-20	2-20	1-20	1-20	1-20	1-20	1-20
Gira	030200	R	600W	1-20	1-20	1-12	1-20					1-20	1-20	1-20	1-20
Gira	030700	R,C	525W	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20
Jung	266 GDE	R	60-600W		1-20	1-20		1-20		1-20			1-20		1-20
Jung	Licht-Management 225 NV DE	RL	100W	1-20	1-20	2-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20
Legrand	617 030		40-600W	6-20	7-20	4-20	6-20	4-20	1-20	4-20	1-20	6-20	7-20	6-20	7-20
Legrand	665714		400W/75W (LED)	1-20	1-10	1-16	1-20	2-20	1-20	2-20	1-20	1-20	1-10	1-20	1-10
merten	MEG5134-0000		4-400W	2-20	2-16	2-20	2-20	1-20	1-20	1-20	1-20	2-20	2-16	2-20	2-16
NIKO	310-02900		200W	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20
NIKO	310-01901	R,L,C,FLi	325W	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20
NIKO	310-0490X		4-200W	1-12	1-8	1-20	1-12	1-20	1-12	1-20	1-12	1-12	1-8	1-12	1-8
NIKO	310-0280X		2-100W	1-6	1-4	1-12	1-6	1-12	1-6	1-12	1-6	1-6	1-4	1-6	1-4
NVC	EP8D11A BLB5		400W	4-20	2-20	4-20	4-20	4-20	1-20	4-20	1-20	4-20	2-20	4-20	2-20
PEHA	431 HAN LED		120W/60W (LED)	1-13	1-8	1-13	1-13	1-20	1-20	1-20	1-20	1-13	1-8	1-13	1-8
PEHA	435 HAB		20-525W	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20
Panasonic	BS EN 60669-2-1		150W-500W	1-4	5-12		1-4	3-8	1-8	3-8	1-8	1-4	5-12	1-4	5-12
Panasonic	WEG578153		80-500W	1-20	4-20		1-20	3-9	1-9	3-9	1-9	1-20	4-20	1-20	4-20
SIEMENS	5UH8222-3NC01		40W-500W	1-20	1-20	1-20	1-20	3-20	1-20	3-20	1-20	1-20	1-20	1-20	1-20
Wintop	13212	L	300W	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20
Wintop	13512	RC	500W	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20	1-20

Kompatibilitätsliste Dimmer

Kompatibel: kein Flackern, keine Geräusche

Semi-kompatibel: kein Flackern, ggf. Geräusche

Inkompatibel: ggf. Flackern, ggf. Geräusche

Dimmer brand	Model	Type	Max. load	GU10			LED Module Clio GEN2		LED Ceiling Light Apollo	T5 Batten DIM	
				3,2W	5,2W	7,5W	22W	36W	22W	9W	18W
											
Berker	286610	RL	500W	1-10	1-3		1-4	1-3	1-4	1-6	1-3
Berker	2819	R	400W	1-7	1-4		1-1	1-1	1-1	1-3	1-3
Berker	283010	R	400W	1-10	1-3	1-10	1-2	1-1	1-2	1-3	1-3
Busch Jaeger	2247U	RL	500W	1-10	1-3	1-10	1-4	1-3	1-4	1-6	1-6
Busch Jaeger	2250U	R	600W	1-10	1-5	1-10	1-5	1-3	1-5	1-6	1-5
Busch Jaeger	6513 U-102	RC	40-420W	2-10	1-10	1-10	1-6	1-4	1-6	1-9	1-5
Busch Jaeger	6523U	R,L	100W	1-10	1-5	1-10	1-1	1-2	1-1	1-1	1-1
Busch Jaeger	6523 U-102	R,C	250W	1-10	1-10	1-10	1-1	1-1	1-1	1-1	1-1
Bticino	N4411N		400W/75W(LED)	1-20	1-14	1-10	1-3	1-2	1-3		
BULL	B6GD100		200W								
Druck	8095	RL	400W	1-10	1-10	1-10	1-2	1-2	1-2	1-3	1-3
EFAPEL	21212		250W/85W(LED)	1-20			1-1	1-1	1-1		
EFAPEL	21214		110W/35W(LED)	1-10							
EFAPEL	21215		150W/50W(LED)				1-2		1-2		
EFAPEL	21216		5-150W(LED)								
EPV	PAB 315		315W	1-8	1-13	1-11					
Feller	40200 LED FMI 61		400W	1-11	1-17	1-14	1-5	1-3	1-5		
Feller	40600 RL FIM61		40-600W	1-5	1-7	1-9	1-4	1-2	1-4		
Feller	40300 RC FMI 61		20-300W	1-11	1-17	1-14	1-5	1-3	1-5		
Feller	40600 RLC FMI 61		20-600W	1-8	1-7	1-9	1-4	1-3	1-4		
Gira	1176 00/104	R,L,C	420W	1-10	1-10	1-10	1-2	1-2	1-2	1-18	1-12
Gira	2262 00/101	R,L	500W	1-10	1-10	1-10	1-5	1-3	1-5	1-6	1-6
Gira	030200	R	600W	1-10	1-3	1-10	1-5	1-3	1-5	1-6	1-6
Gira	030700	R,C	525W	1-10	1-10	1-10	1-5	1-4	1-5	1-23	1-16
Jung	266 GDE	R	60-600W	1-10	1-7	1-10	1-4	1-3	1-4	1-6	1-6
Jung	Licht-Management 225 NV DE	RL	100W	1-10	1-5	1-10				1-6	1-6
Legrand	617 030		40-600W	2-7			1-2		1-2		
Legrand	665714		400W/75W(LED)	1-20	1-14	1-10	1-3	1-2	1-3		
merten	MEG5134-0000		4-400W	1-11	1-17	1-20	1-5	1-3	1-5		
NIKO	310-01901	R,L,C,CFLi	325W	1-8	1-13	1-8	1-4	1-3	1-4	1-13	1-9
NIKO	310-0190X		5-325W	1-8	1-13	1-10	1-4	1-3	1-4		
NVC	EP8D11A BLB5		400W	1-2	1-2	1-2	1-1	1-1	1-1		
NIKO	310-02900		200W	1-2	1-2	1-2	1-1	1-1	1-1		
OPUS	852,397		110W/35W(LED)	1-10	1-6	1-4					
PEHA	431 HAN LED		120W/60W(LED)	1-13	1-11	1-7	1-2		1-2		
PEHA	435 HAB		20-525W	1-14	1-20	1-20	1-5	1-5	1-5		
Panasonic	BS EN 60669-2-1		150W-500W	1-4	1-3	1-4	1-1	1-1	1-1		
Panasonic	WEG578153		80-500W	1-4	1-2		1-2	1-1	1-2		
SIEMENS	5UH8222-3NC01		40W-500W	1-5		1-4	1-1	1-1	1-1		
Wintop	13212	L	300W				1-2	1-1	1-2	1-2	1-2
Wintop	13512	RC	500W	1-10	1-10	1-10	1-7	1-4	1-7	1-22	1-16